

LED MODULES

CONSTANT CURRENT

Options for performance and flexibility

9mm LES

CRI 80+



| | Lumen Output (Lm) | Drive Current (mA) | Total Circuit Power (W) | Colour Temperature | | | | |
|--------------------|-------------------|--------------------|-------------------------|-----------------------|-----------------------|----------------------------------|-----------------------|-----------------------|
| | | | | 2700K | 3000K | | 3500K | 4000K |
| Vibrancy V8 | 500 Lm | 250 mA | 7 | <input type="radio"/> | <input type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> | <input type="radio"/> |
| | 700 Lm | 350 mA | 10 | <input type="radio"/> | <input type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> | <input type="radio"/> |
| | 1000 Lm | 500 mA | 13.5 | <input type="radio"/> | <input type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> | <input type="radio"/> |
| | 1300 Lm | 700 mA | 18.5 | <input type="radio"/> | <input type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> | <input type="radio"/> |
| | 2000 Lm | 1050 mA | 33 | <input type="radio"/> | <input type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> | <input type="radio"/> |

9mm LES

True Colour Elite 98



| | Lumen Output (Lm) | Drive Current (mA) | Total Circuit Power (W) | Colour Temperature | | | | |
|---------------------|-------------------|--------------------|-------------------------|-----------------------|-----------------------|----------------------------------|-----------------------|-----------------------|
| | | | | 2700K | 3000K | | 3500K | 4000K |
| Vibrancy V95 | 500 Lm | 350 mA | 9.6 | <input type="radio"/> | <input type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> | <input type="radio"/> |
| | 700 Lm | 500 mA | 13.5 | <input type="radio"/> | <input type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> | <input type="radio"/> |
| | 1000 Lm | 700 mA | 18.5 | <input type="radio"/> | <input type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> | <input type="radio"/> |
| | 1300 Lm | 1050 mA | 27 | <input type="radio"/> | <input type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> | <input type="radio"/> |
| | 2000 Lm | 1400 mA | 45 | <input type="radio"/> | <input type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> | <input type="radio"/> |

19mm LES

CRI 80+



| | Lumen Output (Lm) | Drive Current (mA) | Total Circuit Power (W) | Colour Temperature | | | | |
|--------------------|-------------------|--------------------|-------------------------|-----------------------|-----------------------|----------------------------------|-----------------------|-----------------------|
| | | | | 2700K | 3000K | | 3500K | 4000K |
| Vibrancy V8 | 500 Lm | 250 mA | 5.2 | <input type="radio"/> | <input type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> | <input type="radio"/> |
| | 700 Lm | 350 mA | 7.6 | <input type="radio"/> | <input type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> | <input type="radio"/> |
| | 1000 Lm | 500 mA | 11 | <input type="radio"/> | <input type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> | <input type="radio"/> |
| | 1300 Lm | 700 mA | 14.5 | <input type="radio"/> | <input type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> | <input type="radio"/> |
| | 2000 Lm | 700 mA | 23.5 | <input type="radio"/> | <input type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> | <input type="radio"/> |
| | 3000 Lm | 1050 mA | 33 | <input type="radio"/> | <input type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> | <input type="radio"/> |
| | 4000 Lm | 1400 mA | 44 | <input type="radio"/> | <input type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> | <input type="radio"/> |
| | 5000 Lm | 1400 mA | 54 | <input type="radio"/> | <input type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> | <input type="radio"/> |

19mm LES

True Colour Elite CRI 98



| | Lumen Output (Lm) | Drive Current (mA) | Total Circuit Power (W) | Colour Temperature | | | | |
|---------------------|-------------------|--------------------|-------------------------|-----------------------|-----------------------|----------------------------------|-----------------------|-----------------------|
| | | | | 2700K | 3000K | | 3500K | 4000K |
| Vibrancy V95 | 500 Lm | 250 mA | 6.7 | <input type="radio"/> | <input type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> | <input type="radio"/> |
| | 700 Lm | 350 mA | 9.7 | <input type="radio"/> | <input type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> | <input type="radio"/> |
| | 1000 Lm | 500 mA | 13.9 | <input type="radio"/> | <input type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> | <input type="radio"/> |
| | 1300 Lm | 700 mA | 18.5 | <input type="radio"/> | <input type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> | <input type="radio"/> |
| | 2000 Lm | 1050 mA | 28.5 | <input type="radio"/> | <input type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> | <input type="radio"/> |
| | 3000 Lm | 1050 mA | 38 | <input type="radio"/> | <input type="radio"/> | <input checked="" type="radio"/> | <input type="radio"/> | <input type="radio"/> |

19mm LES

Beauty B95



| | Lumen Output (Lm) | Drive Current (mA) | Total Circuit Power (W) | Colour Temperature | | | | |
|--|-------------------|--------------------|-------------------------|-----------------------|-------|--|-------|-------|
| | | | | 2700K | 3000K | | 3500K | 4000K |
| | 500 Lm | 250 mA | 6.7 | <input type="radio"/> | | | | |
| | 700 Lm | 350 mA | 9.7 | <input type="radio"/> | | | | |
| | 1000 Lm | 500 mA | 13.9 | <input type="radio"/> | | | | |
| | 1300 Lm | 700 mA | 18.5 | <input type="radio"/> | | | | |
| | 2000 Lm | 1050 mA | 28.5 | <input type="radio"/> | | | | |